



INVERTER PRO 3000 E

PORTABLE POWER

50Hz range Prestige

PRODUCT ADVANTAGES

- Ergonomic, light and compact equipment
- Very Silent
- Quality current
- 12 V output

Zoom

Top of the range equipment that is efficient and with low noise emissions, for a wide range of standard requirements.

Divers

Top of the range equipment that is efficient and with low noise emissions, for a wide range of standard requirements.



This product is QUALIGEN certified. Defined by the SIMOTHERM and GIGREL professional organisations, the QUALIGEN charter is intended to provide a label for equipment compliant with current regulations (user safety, noise level, power, sales information, After Sales Service) in order to provide the highest level of quality of our and thus to guarantee the users safety.

INVERTER PRO 3000 E

GENERAL SPECIFICATIONS

Range	Prestige
Frequency (Hz)	50
Max. power (LTP) (kW)	3
Max power. (LTP) (kVA)	3
Nominal voltage (V)	230
Number of phase	Single phase - 230V
Guaranteed acoustic power Lw(A)	88
Noise level dB(A) - 1m	73.49059891880320
Sound level dB(A) - 7m	58.85701967090160

ENGINE SPECIFICATIONS

Engine type	MZ175
Distribution	O.H.V.
Start	Electrical
Fuel	Petrol (unlead)
Autonomy (h)	10
Consumption (L/h)	1.30
Tank (L)	13
Oil Guard	Yes
Capacity (cm3)	171
Oil capacity (L)	0.60

ALTERNATOR SPECIFICATIONS

Type	Inverter
Regulation	Electronic
Protection class	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

2 sockets 230V 10/16A - circuit breaker + 1 socket 12V 12A - circuit breaker + indicator

DIMENSIONS AND WEIGHT

Length (cm)	68
Width (cm)	44.50
Height (cm)	55.50
Dry Weight (kgs)	68

PACKAGING

Packaging type	Box
Length (cm)	74.10
Width (cm)	55.10
Height (cm)	63.70
Number of box by pallet	2
Pallet height (cm)	67.70

ACCESSORIES SUPPLIED



Spark plug spanner

User and maintenance manual

OPTIONS



R05M Manual changeover switch

The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.



RPM Set of male plugs RPM

Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V



RPQ Earth spike RPQ

For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm² cable.